



SLM500L 400 SDM450 CPU 14nm FinFET 64bit ARM 8 A53
4*1.8GHz Decode/encode 4K@30fps H.265 FHD ISP Android
10 2GB+16GB 3GB+32GB LTE Cat4 150Mbps
50Mbps TD-LTE/FDD-LTE/WCDMA/EVDO/TD-SCDMA/CDMA/GSM GNSS 2.4&5G
WIFI

SLM500L SLM500L-C SLM500L-E* SLM500L-A* SLM500L-LA* SLM500L-
J* SLM500L-AU* SNM500L.

SLM500L 2.4G/5G WiFi BT GPS 1300W 3D
POS VR Camera

LTE Cat 4
150Mbps



FHD 1920x1200 @60pfs

ISP 13M+13M

21MP camera

GNSS

4K @30fps

/

SLM500L-C

LTE FDD: B1/B3/B5/B8

LTE TDD: B34/B38/B39/B40/B41

WCDMA: B1/B8

TD-SCDMA: B34/B39

EVDO/CDMA: BC0

GSM: 900/1800MHz

/ /

SLM500L-E

LTE FDD: B1/B3/B5/B7/B8/B20/B28A

LTE TDD: B38/B40/B41

WCDMA: B1/B5/B8

GSM: 850/900/1800/1900MHz

SLM500L-A*

LTE FDD: B2/B4/B5/B7/B12/B13/B17/B25/B26/B66

WCDMA: B2/B4/B5/B8

GSM: 850/1900MHz

/ /

SLM500L-AU*

LTE FDD: B1/B3/B5/B7/B8/B28

LTE TDD: B40

WCDMA: B1/B5/B8

GSM: 850/900/1800MHz

SLM500L-J*

LTE FDD: B1/B3/B8/B18/B19/B26

LTE TDD: B41

WCDMA: B1/B6/B8/B19

SLM500L-LA*

LTE-FDD: B2/B4/B5/B7/B8/B25/B28/B66

LTE TDD: B40

WCDMA: B2/B5/B8

GSM: 850/900/1900MHz

SNM500L

Wi-Fi & BT

LTE:

Cat 4 FDD: 150Mbps (DL)/50Mbps (UL)

Cat 4 TDD: 117Mbps (DL)/30Mbps (UL)

UMTS:

DC-USDPA: 42Mbps (DL)

HSUPA: 5.76Mbps (UL)

WCDMA: 384Kbps (DL/UL)

TD-SCDMA:

4.2Mbps (DL)/2.2Mbps (UL)

DMA: 5.023/3.084/192 0 Td(/)Tj7/